

BEST AVAILABLE COPY



G-B04/03540



INVESTOR IN PEOPLE

The Patent Office  
Concept House  
Cardiff Road  
Newport  
South Wales  
NP10 8QQ

REC'D 06 SEP 2004

WIPO

PCT

## PRIORITY DOCUMENT

SUBMITTED OR TRANSMITTED IN  
COMPLIANCE WITH RULE 17.1(a) OR (b)

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.

Signed

*He Behen*

Dated

24 August 2004

**THIS PAGE BLANK (USPTO)**

THE PATENT OFFICE

The Patent Office

15 AUG 2003

16AUG03 EB30657-1 002831  
P01/7700 0.00-0319201.0

**Request for grant of a patent**

(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)

The Patent Office

Cardiff Road  
Newport  
South Wales  
NP9 1RH

1. Your reference

57.0588 GB NP

15 AUG 2003

2. Patent application number

(The Patent Office will fill in this part)

0319201.0

3. Full name, address and postcode of the or of each applicant (underline all surnames)

WesternGeco Limited  
Schlumberger House  
Buckingham Gate  
Gatwick  
West Sussex RH6 0NZ  
United Kingdom

Patents ADP number (if you know it)

If the applicant is a corporate body, give the country/state of its incorporation

United Kingdom

8168981001

4. Title of the invention

MULTI-COMPONENT SEISMIC DATA PROCESSING

5. Name of your agent (if you have one)

"Address for service" in the United Kingdom to which all correspondence should be sent (including the postcode)

Akram K. Mirza  
Intellectual Property Law Department  
Schlumberger Cambridge Research Limited  
High Cross  
Maddingley Road  
Cambridge CB3 0EL  
United Kingdom

Patents ADP number (if you know it)

4433504002

6. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and (if you know it) the or each application number

Country

Priority application number  
(if you know it)

Date of filing  
(day / month / year)

7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application

Number of earlier application

Date of filing  
(day / month / year)

8. Is a statement of inventorship and of right to grant of a patent required in support of this request? (Answer 'Yes' if:

YES

- a) any applicant named in part 3 is not an inventor, or
  - b) there is an inventor who is not named as an applicant, or
  - c) any named applicant is a corporate body.
- (See note (d))

## Patents Form 1/77

9. Enter the number of sheets for any of the following items you are filing with this form.  
Do not count copies of the same document

Continuation sheets of this form

Description 28

Claim(s)

Abstract

Drawing(s) 7

10. If you are also filing any of the following, state how many against each item.

Priority documents

Translations of priority documents

Statement of inventorship and right to grant of a patent (Patents Form 7/77)

Request for preliminary examination and search (Patents Form 9/77)

Request for substantive examination (Patents Form 10/77)

Any other documents (please specify)

11. I/We request the grant of a patent on the basis of this application.

Signature

Date

14 August 2003

12. Name and daytime telephone number of person to contact in the United Kingdom

Akram K. Mirza  
01223 325268

### Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

### Notes

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.
- Write your answers in capital letters using black ink or you may type them.
- If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
- If you have answered 'Yes' Patents Form 7/77 will need to be filed.
- Once you have filled in the form you must remember to sign and date it.
- For details of the fee and ways to pay please contact the Patent Office.

## MULTI-COMPONENT SEISMIC DATA PROCESSING

The present invention generally relates to apparatus and methods for processing multi-component (3C/4C) seismic data based on the use of receiver functions, more specifically two-dimensional receiver functions. It also pertains to the use of receiver functions to process and interpret seismic signals to derive an earth image away from the near-surface structure at the receiver location.

### BACKGROUND OF THE INVENTION

The processing and interpretation of multicomponent (3C/4C) seismic data, acquired directly at the seafloor or during 3C land seismic surveys is compromised by the effects that the shallow subsurface has on the deeper reflected wavefield. The near surface is generally associated with low, laterally varying shear wave velocities and on land, the P-wave velocity can also be low. These properties often lead to large P- and S-wave traveltime perturbations in the deeper reflected wavefield which vary from receiver to receiver. In addition, there are suggestions that scattering and anelastic attenuation (especially shear) impacts amplitudes and recorded waveforms as well.

The receiver function methodology has its roots in earthquake seismology, where it was developed to investigate the structure of the crust and upper mantle using multicomponent teleseismic body wave data. Certain aspects of receiver functions are described for example by T. Ryberg and M. Weber in Geophys. J. Int. 141 (2000), 1-11. Reference to aspects of receiver function can also be found in the published patent applications GB 2384557 and WO 02/059647.

While trying to image discontinuities in upper mantle using receiver functions, it was realised that the change in the traveltime difference between the P-wave and the PS-converted wave, as a function of the angle of incidence, could no longer be neglected. T. Ryberg and M. Weber proposed to calculate a velocity spectrum stack (VSS) based on the change in the traveltime difference (hereafter called moveout) in a single layer to find optimal velocities for stacking of receiver functions. Although this approach gives good results when the structure is relatively homogeneous above the converting interface, it lacks a theoretical basis when applied to layered media with significant other discontinuities above the converting interface, i.e. when ray bending is likely to produce significant deviations from the traveltime difference equation for a single layer. This was partly recognised and, subsequently, it was suggested to substitute the average vertical P- and S-wave slowness for a stack of layers, into the equation for a single layer. It was also proposed to circumvent this problem by assuming a reference model (providing an initial  $v_p(z)$  and  $v_s(z)$ ) and a corresponding one-parameter family of related models by multiplying the reference model by a fraction close to one, and obtain the difference in traveltime as a function of slowness by ray-tracing through the perturbed reference model. This approach severely restricts the number of free parameters. Reference to aspects of receiver function can also be found in the published patent applications GB 2384557 and WO 02/059647.

On the other hand, normal moveout correction (NMO), velocity analysis and stacking of multichannel data has a long history in exploration and production seismic and the theory is well developed for horizontally layered media. It was

demonstrated how to derive a power series approximation of the squared reflection traveltime as a function of even powers of offset (i.e. of the form:  $t^2 \approx c_1 + c_2 \cdot x^2 + c_3 \cdot x^4 + \dots$ , where  $t$  denotes two-way traveltime,  $x$  denotes offset and the coefficients depend on layer thicknesses and velocities of the medium). Hyperbolic approximations were used, truncating the infinite series after the second term and defined the rms-velocity as the square-root of the inverse of coefficient  $c_2$ . It is also known that the slope of the  $x^2$ - $t^2$  curve at  $x=0$  yields the inverse of the squared rms-velocity and how from the rms-velocity at two consecutive depth levels the interval velocity between them can be calculated. Taner and Koehler in: Geophysics 34 (1969), 859-881 also introduced the velocity spectrum stacking technique using a multichannel coherence measure called semblance. The work by Taner and Koehler was generalised for PS-converted waves by Tessmer and Behle in Geophys. Prosp. 36 (1988), 671-688, who also derive a Dix-Krey type formula, relating rms-velocities for PS-converted waves to products of P- and S-wave interval velocities in each layer.

In view of the above state of art, it is an object of the present invention to extend and improve the use of receiver functions to process and interpret seismic data to derive images of an earth. It is further object of the invention to determine velocities or velocity models from such receiver functions.

#### SUMMARY OF THE INVENTION

This invention describes systematic approximations of the difference in traveltime between a seismic signal in an

unchanged mode and a corresponding mode-converted signal, such as P-waves (or S-waves) and PS-waves (or SP-waves), converted upon reflection or transmission at a particular interface in a horizontally layered medium or a multi-layered earth model. As such, the relations of the present invention can be used to approximate the moveout of events in receiver functions, which correspond to traveltime differences between non-converted and converted waves. The receiver function can thus be corrected for moveout in the slowness domain or in the time-space domain. The moveout correction overcomes limitations of known attempts to use receiver function to interpret an earth, which attempts were limited to shallow subsurface layers or cases of low-velocity layers (or vertical or near-vertical raypaths).

In a first aspect the traveltime difference is expanded into increasing even powers of slowness, leading to a generalised small-slowness approximation of receiver function moveout in the time-slowness domain. This result is more general than previous results by Ryberg and Weber (2000) since it applies to a stack of layers and contains their results as the special case of a single layer over a halfspace. A pseudo rms-velocity is defined and this leads naturally to a Dix-Krey type relation for receiver functions, relating the pseudo rms-velocities for two consecutive interfaces to the product of the P- and S-wave interval velocity between them.

In a second aspect, a related expansion of the squared traveltime difference is made into increasing even powers of the difference in horizontal travel distance between the P- and PS-converted wave (e.g.,  $dt^2 = c_1 + c_2 \cdot dx^2 + c_3 \cdot dx^4 + \dots$  where  $dt$  denotes the difference in traveltime between the PS-

converted wave and the P-wave from a particular interface, whereas  $dx$  denotes the difference in offset of emergence between the P- and PS-wave). In connection with this expansion, a new type of receiver function is also introduced, formed by two-dimensional deconvolution of  $(x,t)$  domain vertical component data (i.e. P-waves) out of the corresponding  $(x,t)$  radial component data (PS-waves). This 2D-receiver function, because of the added deconvolution in the spatial direction, gives precisely the time-lag between the PS-wave and the P-wave as a function of the distance-lag between them. The second (truncated) expansion hence can be used to NMO correct the new type of receiver function. Synthetic data generated with a reflectivity code is used to illustrate the moveout approximations and the new type of receiver function.

The derived series approximations (and corresponding two-term truncations) of traveltimes differences between PS-converted waves and P-waves from interfaces in horizontally layered media, being either a function of slowness or a function of the difference in horizontal distance traveled by the two phases, enable velocity analysis and subsequent normal moveout correction of events in receiver functions. The derived Dix-Krey type formulas for receiver functions relate the (pseudo) rms-velocities for two consecutive interfaces in a layered earth to the product of P- and S-wave interval velocities between them. A new kind of receiver function is proposed, calculated by two-dimensional deconvolution of  $(x,t)$  domain vertical component data out of  $(x,t)$  radial component data, which gives information about the traveltimes difference between P- and PS-converted phases as a function of the difference in horizontal distance

traveled by those phases. The second moveout approximation applies to events in this new type of receiver function.

Aspects of the invention further include a method of  
5 calculating the moveout (or change as a function of slowness) of the traveltime difference between a PS-converted wave and a P-wave, reflected/transmitted from the same interface in a layered earth, by expanding the traveltime difference into an infinite series of increasing,  
10 even, powers of slowness. This approximation can be made increasingly accurate by including more terms in the expansion. Coefficients of higher-order terms can be obtained by regression analysis of picked traveltime differences in the ( $t, p$ ) domain receiver functions.

15 Another aspect of the invention is a two-term truncation of the series expansion of the traveltime difference between a PS-converted wave and a P-wave reflected/transmitted from the same interface and the association of the coefficient  
20 multiplying the second term with a pseudo rms-velocity. This approximation expresses the moveout of the traveltime differences in terms of a single profile or parameter of scalar quantities with depth rather than two profiles such as the P- and S-wave velocity profiles  $V_p(z)$  and  $V_s(z)$ .

25 Yet another aspect of the invention is a method of velocity analysis of receiver functions calculated by deconvolution or crosscorrelation of vertical component data (or any P-wave quantity) with radial component data (or any S-wave  
30 quantity) in the ( $t, p$ ) domain, which uses the above two-term approximation and any multichannel coherency measure, similar to the velocity analysis method proposed by Taner

and Koehler (1969) for P-wave data or other known methods.

Yet another aspect of the invention is a method of processing the (pseudo-) velocities produced by the method of receiver function velocity analysis, as described above, to obtain the product of P- and S-wave propagation velocities in each layer of the medium, using the Dix-Krey type relations developed for the ( $\tau$ , $p$ ) domain receiver functions.

Yet another aspect of the invention is method of correcting the events in a ( $\tau$ , $p$ ) domain receiver function for the NMO of the traveltimes difference using the product of the P- and S-wave interval velocities obtained using the method described above and a priory knowledge of either the P- or S-wave velocity or velocity ratio in each layer and theoretical expressions or ray-tracing.

Another aspect of the invention is a method of calculating two-dimensional (2D) receiver functions, by 2D (stabilised) deconvolution or crosscorrelation of ( $x$ , $t$ ) domain vertical component data (or any P-wave quantity) with the corresponding ( $x$ , $t$ ) domain radial component data (or any S-wave quantity).

Yet another aspect of the invention is a method of calculating the moveout (or change as a function of the difference in horizontal distance traveled) of the traveltimes difference between a PS-converted wave and a P-wave reflected/transmitted from the same interface, by expanding the squared traveltimes difference into an infinite series of increasing powers of the difference in horizontal

distance traveled by both phases. Since the result is an asymptotic expansion (around  $dx=0$ ), including more terms in the expansion does not necessarily improve the accuracy. The expansion is truncated one term before the smallest  
5 which guarantees that the error in the expansion is of the order of the first neglected term.

Yet another aspect of the invention is a method of calculating a similar asymptotic expansion as above around a  
10 different expansion point (e.g.  $dx=250m$ ) while maintaining the possibility to interpret the first few coefficients as the vertical incidence traveltime and the rms-velocity respectively.

15 Yet another aspect of the invention is a two-term truncation of the series expansion of the squared traveltime difference as a function of increasing even powers of the difference in horizontal distance traveled by the two phases and the association of the coefficient multiplying the second term  
20 with a rms-velocity.

Yet another aspect of the invention is a method of velocity analysis of the 2D-receiver functions formed by two-dimensional deconvolution using the two-term truncation of  
25 the traveltime difference as a function of the difference in horizontal distance traveled and a coherency measure, similar to the velocity analysis method proposed by Taner and Koehler (1969) for P-wave data.

30 Yet another aspect of the invention is a method of processing the velocities produced by the method of receiver function velocity analysis to obtain the product of P- and

S-wave propagation velocities in each layer of the medium, using the Dix-Krey type relations developed for the  $(x,t)$  domain two-dimensional receiver functions.

- 5 Yet another aspect of the invention is a method of correcting the events in a two-dimensional receiver function for the NMO of the traveltime difference using the product of the P- and S-wave interval velocities obtained using the above-described method and a priori knowledge of either the
- 10 P- or S-wave velocity or velocity ratio and theoretical expressions or ray-tracing.

The methods of the invention, including the moveout corrected receiver functions or the velocities derived from

15 the related Dix-Krey relations, can be applied to many known seismic data processing methods, including velocity analysis, moveout correction (NMO and/or DMO), stacking and pre- or post-stack migration.

- 20 These and other aspects of the invention will be apparent from the following detailed description of non-limitative examples and drawings.

#### BRIEF DESCRIPTION OF THE DRAWINGS

- 25 FIG 1 is a schematic illustration of the phases and raypaths involved in the seismological receiver function setting. A plane P-wave is incident on a stack of  $n$  horizontal layers from below and mode-converts to Shear at discontinuities within, and at the base of
- 30 the stack. P-waves are denoted by solid lines, S-waves by dashed lines. The data from each multicomponent station is processed separately and

the extra time  $T_h$  is treated implicitly in the traveltime difference calculation.

FIG. 2 is a schematic illustration of the phases and raypaths involved in the reflection seismic receiver function setting. A P-wave is incident on a stack of  $n$  horizontal layers from above and mode-converts to Shear upon reflection at discontinuities within and at the base of the stack. P-waves are denoted by solid lines, S-waves by dashed lines. The data is recorded on an array of equidistant multicomponent receivers and the difference  $dx$  in horizontal distance traveled by the P- and PS-converted wave from the same reflection/conversion point can be treated explicitly, analogous to the difference in traveltime between the two phases.

FIG. 3 shows pre-processed reflectivity data for the six-layer over a halfspace model (medium properties in Table 1 below). The primary P- and PS-converted waves have been identified by ray-tracing through the model and are indicated in blue and red respectively. This is the data input for receiver function calculation in the slowness domain.

FIG. 4A are receiver functions obtained by stabilised deconvolution of the upgoing P-waves out of the upgoing PS-converted waves shown in FIG.3. The theoretical traveltime differences between the PS-converted waves and primary P-reflections are calculated by ray-tracing and are shown in blue. The two-term approximation (eq. 5) using exact pseudo

rms-velocities is shown in cyan. The black box denotes the area which is shown in detail in FIG. 5A.

FIG. 4B are NMO corrected receiver functions using the two-term approximation (eq. 5) and the linearly interpolated exact pseudo rms-velocity model. The predicted residual moveout is shown in blue. The black box denotes the area which is shown in detail in FIG. 5B.

FIG. 5A is a zoom-in on the area denoted by the black box in FIG. 4A. The two main events correspond to the relative moveout between the P-reflection and its PS-conversion at the fifth and sixth interface. It is showing receiver functions obtained by stabilised deconvolution of the upgoing P-waves out of the upgoing PS-converted waves shown in FIG. 3. The theoretical traveltimes differences between the PS-converted waves and primary P-reflections are calculated by ray-tracing and are shown in blue. The two-term approximation (eq. 5) using exact pseudo rms-velocities is shown in cyan.

FIG. 5B is a zoom-in on the area denoted by the black box in FIG. 4B. The two main events correspond to the relative moveout between the P-reflection and its PS-conversion at the fifth and sixth interface. It is showing NMO corrected receiver functions, using the two-term approximation and the linearly interpolated exact pseudo rms-velocity model. The predicted residual moveout is shown in blue.

FIG. 6A is a receiver functions calculated by two-dimensional stabilised deconvolution of  $(x,t)$  domain vertical component data out of the corresponding radial component data. This 2D-Receiver Function gives the traveltime difference between a P-wave reflection and its PS-conversion as a function of the difference in the horizontal travel distance. The theoretical traveltime differences, calculated by raytracing, are indicated in blue. The two-term approximation, calculated from eq. 20 and the coefficients given in 25a,b using exact medium properties, is indicated in cyan.

FIG. 6B shows again theoretical traveltime differences and the two-term approximation are indicated in blue and cyan respectively. Successive higher order approximations are shown in green.

FIG. 7A is a zoom-in on the 2D-Receiver Functions and moveout approximations shown in FIG. 6A. The two main events give information about the difference in traveltime between the P-reflection and its PS-conversion at the fifth and sixth interface as a function of the difference in horizontal distance traveled. Theoretical traveltime differences and the two-term approximation (eq.20) are indicated in blue and cyan respectively.

FIG. 7B is a zoom-in on the 2D-Receiver Functions and moveout approximations shown in FIG. 6B. Successive

higher order approximations are also shown, in green.

## DETAILED DESCRIPTION AND EXAMPLES

5

### Series expansion of the traveltime difference as a function of slowness

It is well known from global seismology that the difference  
10 in traveltime between a P-wave incident on a stack of  $n$  horizontal layers from below and the corresponding PS-wave, converted upon transmission into the stack, can be written:

$$dt = \sum_{k=1}^n h_k \left( \sqrt{Vs_k^{-2} - p^2} - \sqrt{Vp_k^{-2} - p^2} \right), \quad (1)$$

15

where  $h_k$ ,  $Vs_k$  and  $Vp_k$  denote the thickness, shear and compressional wave velocity of layer  $k$  respectively, and  $p$  the slowness of the incident plane-wave. Note that this formula implicitly takes into account the extra time ( $T_h$ ) it  
20 takes the incident plane-wave to reach the horizontally offset PS-conversion at the base of the stack. Hence this formula can be used to compare the arrival time of plane P- and PS-converted waves with the same slowness, arriving at the same receiver, as is normally done in seismology (see  
25 FIG 1). Equation (1) contains terms of the form:  $(1-p^2v^2)^{\frac{1}{2}}$ , where  $v$  can denote either the P- or S-wave velocity. Such terms can be expanded into a Taylor series as follows:

$$(1-p^2v^2)^{\frac{1}{2}} = \sum_{j=0}^{\infty} q_j (p^2v^2)^j = 1 - \frac{1}{2}(p^2v^2) - \frac{1}{8}(p^2v^2)^2 - \frac{1}{16}(p^2v^2)^3 - \dots, \quad (2)$$

30

where the coefficients  $q_j$  are given by:

$$q_0 = 1, \quad q_j = \frac{\frac{1}{2}(\frac{1}{2}-1)(\frac{1}{2}-2)\cdots(\frac{1}{2}-j+1)}{j!}(-1)^j \quad (3)$$

5 Substituting equation (2) into equation (1), the traveltime difference can be written:

$$dt = \sum_{j=0}^{\infty} q_j \sum_{k=1}^n h_k (Vs_k^{2j-1} - Vp_k^{2j-1})(p^2)^j \quad (4)$$

10

Equation (4) is an expansion of the traveltime difference between plane P- and PS-converted waves through an  $n$ -layered medium in increasing even powers of slowness. Note that the accuracy of the expansion is directly related to the accuracy of the substituted Taylor series approximation (equation 2), which means that the product  $p^2 v^2$  should be small (at least smaller than 1, which means that the waves should be nowhere evanescent) throughout the stack. Therefore the product of the highest P-velocity and the slowness determine the accuracy of equation (4). If it is assumed that the slowness is small throughout the stack, we can truncate the infinite series given by eq. (4) after the second term and neglect terms of fourth order in slowness and higher. This gives the small-slowness, or short-spread approximation:

20  
25

$$dt \doteq \sum_{k=1}^n h_k (Vs_k^{-1} - Vp_k^{-1}) + \frac{1}{2} \sum_{k=1}^n h_k (Vp_k - Vs_k) p^2 \quad (5)$$

30 The first term in equation (5) is simply the difference in

traveltime between a vertically incident P- and S-wave ( $p=0$ ) through the stack of layers. The second term, multiplying  $p^2$ , is not simply interpretable since it contains products of layer thicknesses and differences in velocities and has units  $[m^2/s]$ . However, maintaining the analogy with NMO corrections developed in exploration and production seismic, we call this the pseudo rms-velocity. Thus the traveltime difference at vertical incidence  $dt_0$  and the pseudo rms-velocity  $v_{rms}$  respectively can be defined as:

$$dt_0 = \sum_{k=1}^n h_k (Vs_k^{-1} - Vp_k^{-1}), \quad (6a)$$

$$\bar{v}_{rms} = \frac{1}{2} \sum_{k=1}^n h_k (Vp_k - Vs_k). \quad (6b)$$

Note that for a single layer, the short-spread approximation given in equation (5) reduces to the equation given by Ryberg and Weber (2000). Hence, their result is a special case of the small-slowness relation proposed here. Note also that although equation (1) originates from earthquake seismology and is usually only applied in a transmission setting, it is also valid in a reflection setting, where plane P- and PS-waves are considered, reflected and mode-converted at the same interface in a horizontally layered medium and recorded at the same receiver.

#### A Dix-Krey relation for receiver function pseudo rms-velocities

The definition of a pseudo rms-velocity in equation (6b) allows the derivation of a Dix-Krey type formula that relates the pseudo rms-velocities to the product of P- and S-wave interval velocities, as will be shown below. A

similar analysis as Tessmer and Behle (1988) is applied and the thickness  $h_k$  of layer  $k$  is expressed in terms of the one-way vertical traveltimes  $\tau_k^p$  and  $\tau_k^s$  and interval velocities in that layer:

$$h_k = \frac{1}{2}(Vp_k \tau_k^p + Vs_k \tau_k^s). \quad (7)$$

Also, the ratio of vertical one-way traveltimes equals the inverse of the ratio of interval velocities:

$$\frac{\tau_k^p}{\tau_k^s} = \frac{Vs_k}{Vp_k}. \quad (8)$$

If equation (7) is substituted into the definition of the pseudo rms-velocity (eq. 6b) and the identity in eq. (8) is used, one can derive the following expression for the pseudo rms-velocity at layers  $n$  and  $n-1$ :

$$\tilde{v}_{rms}^n = \frac{1}{2} \sum_{k=1}^n (\tau_k^s - \tau_k^p) \cdot Vs_k Vp_k, \quad (9a)$$

$$\tilde{v}_{rms}^{n-1} = \frac{1}{2} \sum_{k=1}^{n-1} (\tau_k^s - \tau_k^p) \cdot Vs_k Vp_k. \quad (9b)$$

Subtracting equation (9b) from equation (9a), one arrives at:

$$Vs_n Vp_n = 2 \cdot \frac{\tilde{v}_{rms}^n - \tilde{v}_{rms}^{n-1}}{(\tau_n^s - \tau_n^p)}. \quad (10)$$

Finally, using that the difference in the vertical one-way S- and P-wave traveltimes through layer  $n$  is equal to the

difference in vertical incidence traveltime differences between layer  $n$  and layer  $n-1$ :

$$(\tau_k^s - \tau_k^p) = dt_0^n - dt_0^{n-1}, \quad (11)$$

5

one arrives at a Dix-Krey type of relation that relates the pseudo rms-velocities to the product of P- and S-wave interval velocities :

$$10 \quad V_s V_p = 2 \cdot \frac{\tilde{v}_{rms}^n - \tilde{v}_{rms}^{n-1}}{dt_0^n - dt_0^{n-1}} \quad (12)$$

Equation (12) says that the product of P- and S-wave interval velocities in layer  $n$  is twice the ratio of the differences in pseudo rms-velocities and vertical incidence traveltime differences. Equation (12) can be verified by directly substituting the definitions of the pseudo rms-velocities and vertical incidence traveltime differences (i.e. eq. 6a,b).

## 20 **Expansion of the traveltime difference as a function of the difference in horizontal distance traveled**

In the previous sections, the horizontal distance between the point of P-wave transmission and PS-conversion at the base of the stack, but emerging at the same surface location, was taken into account implicitly in the derivation of the traveltime difference (equation 1). The main (historical) reason for this is that it allows accurate comparison of P- and PS-wave traveltimes at a single multicomponent station (see FIG 1). However, when the multicomponent data are recorded on a densely spaced array

of receivers, such as in exploration and production seismic, the P- and PS-wave energy originating from the same location on the converting interface are both recorded, although at horizontally offset locations in the receiver array. This  
 5 allows us to consider the difference in traveltimes and in horizontal travel distance explicitly for an array of receivers (compare FIG.1 and FIG. 2)

Using elementary trigonometric relations and Snell's law,  
 10 the explicit difference in traveltimes between a plane P- and PS-wave of slowness  $p$ , transmitted and converted at the same location at the base of layer  $n$ , can be written (where  $h_i$ ,  $V_{s_i}$  and  $V_{p_i}$  denote the thickness, shear and compressional wave velocity of layer  $i$  respectively):

$$dt = \sum_{k=1}^n (Ts_k - Tp_k) = \sum_{k=1}^n \left[ \frac{h_k}{Vs_k \sqrt{1 - p^2 Vs_k^2}} - \frac{h_k}{Vp_k \sqrt{1 - p^2 Vp_k^2}} \right] \quad (13)$$

Similarly, the difference in horizontal distance traveled can be written:

$$dx = \sum_{k=1}^n (Xp_k - Xs_k) = \sum_{k=1}^n \left[ \frac{h_k Vp_k}{\sqrt{1 - p^2 Vp_k^2}} - \frac{h_k Vs_k}{\sqrt{1 - p^2 Vs_k^2}} \right] \quad (14)$$

Now, following the analysis of Tessmer and Behle (1988), both  $dt$  and  $dx$  are expanded into infinite series of even  
 25 powers of  $p$ . Hereby the Taylor series expansion of the function  $(1 - p^2 v^2)^{-1/2}$  is used, where  $v$  can denote both the P- and S-wave velocity.

$$(1-p^2v^2)^{-\frac{1}{2}} = \sum_{j=1}^{\infty} q_j (p^2v^2)^{j-1} = 1 + \frac{1}{2}(p^2v^2) + \frac{1 \times 3}{2 \times 4}(p^2v^2)^2 + \frac{1 \times 3 \times 5}{2 \times 4 \times 6}(p^2v^2)^3 + \dots \quad (15)$$

where the coefficients  $q_j$  are given by:

$$q_1 = 1, \quad q_j = \frac{1 \times 3 \times \dots \times (2j-3)}{2 \times 4 \times \dots \times (2j-2)}, \quad (16)$$

Note that this expansion is the inverse of the expansion used in the previous sections (see equation 2). Thus substituting equation (15) into equations (13) and (14) for both terms containing P- and S-velocities to obtain infinite series for  $dt$  and  $dx$  results in:

$$dt = \sum_{j=1}^{\infty} q_j \sum_{k=1}^n h_k (Vs_k^{2j-3} - Vp_k^{2j-3})(p^{2j-2}), \quad (17a)$$

$$dx = \sum_{j=1}^{\infty} q_j \sum_{k=1}^n h_k (Vs_k^{2j-1} - Vp_k^{2j-1})(p^{2j-1}). \quad (17b)$$

To simplify the appearance of equations (17a,b) and subsequent derivations, the following coefficients are defined:

$$a_m = \sum_{k=1}^n h_k (Vs_k^{2m-3} - Vp_k^{2m-3}), \quad (18a)$$

$$b_m = -q_m a_{m+1}, \quad (18b)$$

$$\gamma_m = q_m a_m. \quad (18c)$$

Using these, equations (17a,b) become:

$$dt = \sum_{k=1}^{\infty} \gamma_k p^{2k-2}, \quad (19a)$$

$$dx = p \sum_{k=1}^{\infty} b_k p^{2k-2}. \quad (19b)$$

Equations 19a,b have the same form as Taner and Koehler (1969) derived for the traveltime and offset of a P-wave reflection in a horizontally layered medium and as Tessmer and Behle (1988) found for the traveltime and offset of PS-converted waves. This suggests that it is possible to apply the same methodology as they have done to find an expansion of the square of the traveltime difference into increasing even powers of the difference in horizontal travel distance. Such an expansion would be useful if a new kind of receiver function could be obtained, where PS-converted waves are shifted both in time and space relative to the P-wave, measuring the traveltime difference as a function of the difference in horizontal distance traveled by both phases. But this new receiver function is exactly the result of applying a two-dimensional (2D) deconvolution of the (x,t) domain vertical component data from the (x,t) domain horizontal component data. Thus, the objective is to express the traveltime difference  $dt$  as:

$$dt^2 = c_1 + c_2 \cdot dx^2 + c_3 \cdot dx^4 + c_4 \cdot dx^6 + \dots, \quad (20)$$

The explicit form of equation (20) can be found by squaring the power series for  $dt$  (equation 19a), successive higher even powers of  $dx$  (equation 19b) and ordering terms of equal powers in slowness  $p$ . Starting by squaring  $dx$ :

$$dx^2 = \left( p \sum_{k=1}^{\infty} b_k p^{2k-2} \right)^2 = p^2 (b_1 + b_2 p^2 + b_3 p^4 + b_4 p^6 + \dots)^2 = \quad (21)$$

$$p^2 (b_1^2 + (b_1 b_2 + b_2 b_1) p^2 + (b_1 b_3 + b_2^2 + b_3 b_1) p^4 + (b_1 b_4 + b_2 b_3 + b_3 b_2 + b_4 b_1) p^6 + \dots) = p^2 \sum_{k=1}^{\infty} B_{k1} p^{2k-2},$$

where,

$$B_{k1} = b_1 b_k + b_2 b_{k-1} + \dots + b_{k-1} b_2 + b_k b_1. \quad (22)$$

The higher, even powers of this series can be found by recursively applying equation (22) to find the coefficients. This leads to the following result:

10

$$dx^{2n} = \sum_{k=1}^{\infty} B_{kn} p^{2k-2}, \quad (23)$$

where,

$$B_{kn} = B_{11} B_{k,n-1} + B_{21} B_{k-1,n-1} + \dots + B_{k-1,1} B_{2,n-1} + B_{k1} B_{1,n-1}. \quad (24)$$

Note that the coefficients  $B_{kn}$  have to be calculated recursively since they contain coefficients  $B_{-,n-1}$ . The same methodology can also be applied to find the square of  $dt$  to find:

20

$$dt^2 = \left( \sum_{k=1}^{\infty} A_k p^{2k-2} \right) = c_1 + c_2 \underbrace{\left( p^2 \sum_{k=1}^{\infty} B_{k1} p^{2k-2} \right)}_{dx^2} + c_3 \underbrace{\left( p^4 \sum_{k=1}^{\infty} B_{k2} p^{2k-2} \right)}_{dx^4} + c_4 \underbrace{\left( p^6 \sum_{k=1}^{\infty} B_{k3} p^{2k-2} \right)}_{dx^6} + c_5 \dots, \quad (25)$$

where,

$$A_k = \gamma_1 \gamma_k + \gamma_2 \gamma_{k-1} + \dots + \gamma_{k-1} \gamma_2 + \gamma_k \gamma_1, \quad (26)$$

Hence, written out up to 6<sup>th</sup> order in  $p$ , equation (25) becomes:

$$A_1 + A_2 p^2 + A_3 p^4 + A_4 p^6 + \dots = c_1 + c_2 B_{11} p^2 + (c_2 B_{21} + c_3 B_{12}) p^4 + (c_2 B_{31} + c_3 B_{22} + c_4 B_{13}) p^6 + \dots$$

Thus the first two coefficients, using equations (18a-c), are

$$c_1 = A_1 = \gamma_1^2 = (q_1 a_1)^2 = \left( \sum_{k=1}^n h_k \left( \frac{1}{V_{s_k}} - \frac{1}{V_{p_k}} \right) \right)^2 \equiv dt_0^2, \quad (27a)$$

$$c_2 = \frac{A_2}{B_{11}} = \frac{2\gamma_1 \gamma_2}{b_1^2} = \frac{a_1}{a_2} = \frac{\sum_{k=1}^n h_k \left( \frac{1}{V_{s_k}} - \frac{1}{V_{p_k}} \right)}{\sum_{k=1}^n h_k (V_{s_k} - V_{p_k})} \equiv \frac{1}{v_{rms}^2} \quad (27b)$$

Note that coefficient  $c_1$  (equation 27a) can be directly interpreted as the square of the difference in traveltime between the P- and PS-converted wave at vertical incidence ( $p=0$  s/m). The coefficient  $c_2$  can not be interpreted so easily, although the numerator is equal to  $dt_0$ , but it has the same form as was found by Tessmer and Behle for PS-converted waves and hence it can be equaled to the inverse of the square of an rms-velocity.

#### A Dix-Krey relation for reflection seismic receiver functions

Analogous to the derivation of a Dix-Krey type relation for the two-term traveltimes difference approximation in the slowness domain, Dix-Krey type relations can also be derived for the approximations of the traveltimes difference as a function of the difference in horizontal distance traveled by the P- and PS-wave. This is the topic of the current section. As will be seen, the result will relate the rms-velocities defined in the previous section to the products of P- and S-wave interval velocities. Starting from the squared rms-velocity:

$$v_{rms}^2 = \frac{\sum_{k=1}^n h_k (V_{S_k} - V_{P_k})}{dt_0^2} \quad (28)$$

and proceeding by substituting equation (7) for the thickness of a layer k and the ratio of one-way vertical traveltimes (equation 8) into equation (28) results in:

$$\sum_{k=1}^n h_k (V_{S_k} - V_{P_k}) = \sum_{k=1}^n \frac{1}{2} (V_{P_k} \tau_k^p + V_{S_k} \tau_k^s) (V_{S_k} - V_{P_k}) = \sum_{k=1}^n (\tau_k^p - \tau_k^s) \cdot V_{S_k} V_{P_k} \quad (29)$$

Hence, combining equation (28) and (29), for layer n and n-1 respectively gives:

$$dt_0^n v_{rms,n}^2 = \sum_{k=1}^n (\tau_k^p - \tau_k^s) \cdot V_{P_k} V_{S_k} \quad (30a)$$

$$dt_0^{n-1} v_{rms,n-1}^2 = \sum_{k=1}^{n-1} (\tau_k^p - \tau_k^s) \cdot V_{P_k} V_{S_k} \quad (30b)$$

Subtracting equation (30b) from equation (30a) leads to the product of P- and S-wave interval velocities in layer n:

$$Vp_n Vs_n = \frac{dt_0^n v_{rms,n}^2 - dt_0^{n-1} v_{rms,n-1}^2}{(\tau_n^p - \tau_n^s)} \quad (31)$$

Now finally, using that:

$$5 \quad (\tau_n^p - \tau_n^s) = dt_0^n - dt_0^{n-1}, \quad (32)$$

equation (31) can be written:

$$10 \quad Vp_n Vs_n = \frac{dt_0^n v_{rms,n}^2 - dt_0^{n-1} v_{rms,n-1}^2}{(dt_0^n - dt_0^{n-1})} \quad (33)$$

Equation (33) is the desired Dix-Krey type relation. It shows how the product of P- and S-wave interval velocities for a layer k, can be calculated once the rms velocities and the vertical incidence time differences for that layer and the previous layer are known. Equation (33) has exactly the same form as found previously for PS-converted waves by Tessmer and Behle (1988). Note however that the vertical incidence traveltime differences and rms velocities are defined differently, as shown in the previous section.

### Numerical examples

In the following it is illustrated how the derived approximations may be used with some numerical examples.

25 **Example 1: Moveout correction using the two-term approximation in the slowness domain**

Synthetic data was calculated using a 2D reflectivity code for a horizontally layered model consisting of 6 homogeneous

layers overlying a halfspace. The medium properties are summarised in Table 1. In the synthetic experiments, 801 receivers were positioned symmetrically about the source position with a receiver-receiver spacing of 3.125m. Thus, 5 the maximum source-receiver offset considered here is 1250m. The sampling rate was 2ms. The source in the modeling was a P-wave point source, positioned on the surface, emitting a 50Hz Ricker wavelet. As pre-processing step the data were transformed to the time-slowness ( $\tau, p$ ) domain. The pre-processed reflectivity data is shown in FIG.3. 10

The receiver functions, calculated by stabilised deconvolution, for this data are shown in FIG. 4A. The theoretical traveltime differences between the PS-converted 15 waves and primary P-reflections are calculated by ray-tracing and are shown in blue. The two-term approximation (eq. 5) using exact pseudo rms-velocities is shown in cyan. It is clear that the two-term approximation is exact at zero slowness ( $p=0$  s/m). Moreover, the accuracy decreases with 20 both increasing slowness and depth. This is because the velocity increases with depth and the accuracy of the expansion is directly related to the product of the velocity and the slowness in each layer. In FIG. 4B, the receiver functions have been NMO corrected using the two-term 25 approximation and the linearly interpolated pseudo rms-velocities. It is clear that all identified events have been significantly flattened. The predicted residual moveout, calculated by extracting the two-term approximation from the ray-traced (exact) traveltime differences, is shown in blue.

30

In FIGs. 5, the area denoted by the black boxes in FIGs.4s, is shown in detail. The two main events correspond to the

relative moveout between the P-reflection and its PS-conversion at the fifth and sixth interface. Again, it is clear that the events have been significantly flattened using the two-term approximation.

5

Note that the moveout correction using the two-term approximation obviously requires a pseudo rms-velocity model. In the example here, the exact pseudo rms-velocities is calculated using eq. 6b and Table 1. The two-term approximation of the traveltime difference makes the problem amendable to velocity analysis (Taner and Koehler, 1969) by reducing the number of parameters to two.

10

Layer	P-velocity [m/s]	S-velocity [m/s]	Depth [m]
1	1650	400	0
2	1775	700	50
3	1900	950	125
4	2000	1000	225
5	2250	1125	425
6	2750	1375	700
7	3000	1500	1300

Table 1 Medium properties of the 6-layer over a halfspace model used in the reflectivity calculations.

15

**Example 2: Moveout approximations of the traveltime difference as a function of the difference in horizontal distance traveled**

20

In this example we use the exactly the same reflectivity data as was used in example 1, with the exception that the input data is not transformed to the time-slowness ( $\tau, p$ ).

domain. Instead, as proposed in the section on series approximation of the traveltime difference as function of the difference in horizontal difference, we calculate a new type of receiver function formed by two-dimensional (2D) deconvolution of the vertical component (upgoing P-waves) out of the radial component (upgoing S-waves) data in the  $(x,t)$  domain. Two-dimensional deconvolution in the  $(x,t)$  domain is equivalent to division of each point in the corresponding frequency-wavenumber  $(f,k)$  domain. Hence, individual plane PS-wave components are shifted in time and space relative to the arrival time and location of the P-wave components with the same frequency and (horizontal) wavenumber.

The result of this 2D-deconvolution is shown in FIG. 6A. The theoretical traveltime differences as function of the difference in horizontal travel distance, calculated by ray-tracing, are shown for each interface in blue. The two-term approximation, calculated from eq. (20) using coefficients eq. (27a,b) and exact medium properties, is shown in cyan. FIG. 6B shows (in green colour) successive higher-order approximations. The coefficients for the higher-order terms have been calculated from eq. (25), repeatedly making use of eq. (22), (24) and (26). Although it is not clear from FIGs. 6 (or FIGs. 7), closer inspection shows that although the higher-order approximations are more accurate for small slownesses, they break down at a lower slowness. This has to do with the asymptotic nature of the series approximation.

Although the 2D-receiver functions in FIG. 6A contain a lot of secondary events which cannot be explained by the ray-traced theoretical traveltime differences for each of the

six interfaces, it is clear that those events that can be related to the interplay of a primary P-reflection and its PS-conversion, are approximated reasonably by the two-term approximation, especially at small-slowness.

5

In FIG. 7A, two events from the 2D-receiver function corresponding to the fifth and sixth interface, are shown in detail. FIG. 7B shows the corresponding zoom-in on the theoretical, two-term and higher-order traveltime difference curves.

10

While the invention has been described in conjunction with the exemplary embodiments described above, many equivalent modifications and variations will be apparent to those skilled in the art when given this disclosure. Accordingly, the exemplary embodiments of the invention set forth above are considered to be illustrative and not limiting. Various changes to the described embodiments may be made without departing from the spirit and scope of the invention.

20




FIG. 1



**THIS PAGE BLANK (USPTO)**




FIG. 2

THIS PAGE BLANK (USPTO)

3/7




FIG. 3

THIS PAGE BLANK (USPTO)




FIG. 4A




FIG. 4B

THIS PAGE BLANK 115770




FIG. 5A




FIG. 5B

THIS PAGE BLANK (USPTO)




FIG. 6A




FIG. 6B

THIS PAGE BLANK (USPTO)




FIG. 7A





FIG. 7B

**PCT/GB2004/003540**



**This Page is Inserted by IFW Indexing and Scanning  
Operations and is not part of the Official Record**

**BEST AVAILABLE IMAGES**

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☐ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☐ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER:** \_\_\_\_\_

**IMAGES ARE BEST AVAILABLE COPY.**

**As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.**